

15 Watt or 30 Watt Public Address Amplifiers

PVL15A 15W P.A. mixer amplifier

PVL30A 30W P.A. mixer amplifier

Features

- Mic1 priority mute function with front button
- Separate bass and treble controls



PVL15A



PVL30A



rear of unit



rear of unit

Specifications

PVL15A

RMS Output Power..... 15W
Max. Output Power..... 30W
AC Power Consumption..... 60W
Power Supply AC 120V, 50/60Hz
Zones..... 1
Speaker Outputs..... 4/8/16 Ohms, 70/25V
Inputs..... 2 x Mic (1/4" and 1/4" or XLR)
1 x Aux (1/4")
Frequency Response 50Hz ~ 15KHz
Tone Control Bass $\pm$ 10dB, Treble $\pm$ 10dB
THD Less than 0.1% @1KHz
Signal/Noise Ratio..... Microphone: >75dB, Line: >80dB
Controls Volume for each source, Tone, Priority
Telephone No
Indicators Power
Dimensions..... 8.25" (W) x 3" (H) x 7.9" (D)
Weight 8.4 lbs.
Listings CE, FCC, RoHS

PVL30A

30W
60W
100W
AC 120V, 50/60Hz
1
4/8/16 Ohms, 70/25V
2 x Mic (1/4" and 1/4" or XLR)
1 x Aux (1/4" or RCA)
50Hz ~ 15KHz
Bass $\pm$ 10dB, Treble $\pm$ 10dB
Less than 0.1% @ 1KHz
Microphone: >75dB, Line: >80dB
Volume for each source, Tone, Priority
No
Power
8.25" (W) x 3" (H) x 7.9" (D)
10.6 lbs.
CE, FCC, RoHS