

ETS

STW7 Audio Surveillance Kit

Electronic Technical Services Inc.
211 Conchas SE
Albuquerque, NM 87123
PH 505-888-3923 FAX 505-888-3926
Website: www.etsnm.com

Description

Four zone, 2 way audio surveillance system. For stand alone applications or for use with DVR's and remote monitoring equipment. Both sides of conversations can be recorded.



Kit Includes

- 4ea. STW1 Microphone/speakers.
- STW4 Base station
- 16vac AC adaptor
- 2 RCA Patch cables.
- Warning labels.

Options

- Call switch button: STW1-C.
- RM1, RM2 rack mounts.

Wiring Requirements

- Microphone and speaker: 2 each stranded 22-gauge, 2-conductor shielded cable. 500' max.
- Call switch: 22-gauge, 2 conductor.

Caution

It is the responsibility of the installation company and end user to comply with state and federal privacy laws regarding the use of audio surveillance equipment. If you are unfamiliar with these laws, consult a qualified attorney. In most cases, posting the provided warning label in plain view is all that is required.

Warranty

1 year parts and labor.

Made in USA

Available from A1 Security Cameras

www.a1securitycameras.com email: sales@a1securitycameras.com

STW1 Mic./speaker Specifications

- Omni-directional element w/25' range.
- Low noise MOSFET pre-amplifier.
- Line level, unbalanced output.
- Adjustable gain.
- Treble boost circuit. Selectable on/off.
- Limiter circuit. Selectable on/off.
- Euro-style connectors makes cable terminations fast and clean.
- Flush mount, standard 2 gang stainless plate.
- Power: 12 VDC @ 10mA.
- 3" .5 watt speaker.
- 70V line speaker input.
- See STW1 data sheet for more information.

STW4 Base Station

- Page mode enables talk back to all 4 zones at once.
- Remote speaker & microphone volume controls.
- Internal talk back microphone
- Master volume control.
- Press to talk button.
- When paged from a zone, that zone is selected automatically for talk back.
- VCR/DVR In/outs can be used to record both sides of the conversation.
- Tape monitor in/out indicator.
- Headphone jack for private listening.
- Euro-style connectors makes cable terminations fast and clean.
- Dimensions: W 6.5 x L 6.5 x H 1.56.
- See STW4 data sheet for more information.